Polarization-multiplexed

continuous-variable quantum key distribution



 State Key Laboratory of Information Photonics and Optical Communications, Beijing University of Posts and Telecommunications, Beijing 100876, China
State Key Laboratory of Advanced Optical Communication, Systems and Networks, Department of Electronics, and Center for Quantum Information Technology, Peking University, Beijing 100871, China Email: zhangyc@bupt.edu.cn

1 Introduction

Quantum key distribution (QKD) promises an implementation of establishing secret keys between two remote parties based on the uncertainty principles of quantum physics [1]. Continuous-variable quantum key distribution (CV-QKD) taking advantage of commercial-accessible components loosens the requirements for extreme operating environment and expensive devices [2,3]. The establishment of the protocol security with discrete-modulation [4-6] makes it a prospective approach to widespread application. In this paper, we propose a polarization-multiplexed CV-QKD protocol with four-state modulation capable of full use of two orthogonal polarization channels and experimentally investigate it. The experiment results show the polarization and phase compensation scheme solves the difficulties of estimating the overall phase rotation for dual-polarization signals, which makes the dual-polarization modulation scheme a superior alternative for its double secret key rate.

2 Experimental setup







Figure 1 Experimental setup of proposed polarization-multiplexed CV-QKD scheme.

- 5MHz repletion rate, 1550nm narrow linewidth laser, random key data sequence of 2¹⁰, mean photon number of 0.1 per symbol
- First and second reference data sequences of 50, signal data sequences of 1024 per calculation period
- Sampling rate of 100MHz, oversampling factor of 20

3 Phase compensation scheme

□ Introduce a pair of reference $(X_1, X_2, Y_1, Y_2)^T$ and $(X_3, X_4, Y_3, Y_4)^T$, where

First group				Second group			
X		Y		X		Y	
X	p	X	p	x	p	x	p
<i>X</i> ₁	<i>X</i> ₂	<i>Y</i> ₁	<i>Y</i> ₂	<i>X</i> ₃	X_4	<i>Y</i> ₃	Y_4

 $\square \text{ Matrix } A_R \text{ consisting of reference data should be full-rank, where} \\ A_R = \begin{pmatrix} X_1 & X_2 & Y_1 & Y_2 \\ X_2 & -X_1 & Y_2 & -Y_1 \end{pmatrix}$

$$\begin{bmatrix} X_{3} & X_{4} & Y_{3} & Y_{4} \\ X_{4} & -X_{3} & Y_{4} & -Y_{3} \end{bmatrix}$$

Use reference data A_R and detected reference data M_R to calculate a overall rotation matrix S through M_R = SA_R.
Compensate polarization mixing and relative phase by rotating Bob's received data using S.

4 **Results**

- After Bob's detection, 10⁶ sampling points of x/p quadrature on dual polarization are divided into 43 groups each including reference and key part.
- □ Bob's received reference data (top) is recovered (bottom) as Alice encodes (-1,1) and (1,1) on X polarization, and (1,1) and (-1,1) on Y polarization's first and second reference signals as shown in Fig. 2(a).
- □ Method in [2, 3] is adopted to calculate the secret key rate of four-state protocol $K_{DP} = 2K_{SP}$, $K_{SP} = \beta I (M_A: H_B) \sup S_{BE}^G(\kappa_{AB})$.
- Phase distortion and polarization mixing of received signals are simultaneously compensated before normalization by shot-noise variance as shown in Fig. 2.



5 Conclusion

We experimentally demonstrate a dual-polarization modulated CV-QKD system for the first time. The results show that combined with our efficient polarization and phase compensation scheme, this low-complexity scheme can further improve the secret key rate and prompt CV-QKD to be network-compatible [7] and on-chip integrated [8].

Reference

- [1] S. Pirandola *et al.*, arXiv:1906.01645 (2019).
- [2] Y. Zhang *et al.*, Quantum Sci. Technol. 4, 035006 (2019).
- [3] Y. Zhang et al., Phys. Rev. Lett. 1, 010502 (2020).
- [4] S. Ghorai et al., Phys. Rev. X 9, 021059 (2019).
- [5] J. Lin et al., Phys. Rev. X 9, 041064 (2019).
- [6] Z. Li *et al.*, arXiv:1805.04249 (2018)
- [7] A. Aguado *et al.*, IEEE Commun. Mag. 57, 20–26 (2019).
- [8] G. Zhang et al., Nat. Photonics 13, 839-842 (2019).